

01-07-00

A

01/05/00
jc714 U.S. PTO**IN THE UNITED STATES PATENT AND TRADEMARK OFFICE****CERTIFICATE OF MAILING**

This transmittal and the documents and/or fees itemized hereon and attached hereto have been deposited as "Express Mail Post Office to Addressee" in accordance with 37 C.F.R. § 1.10 with Express Mail Mailing Label Number EL302635146US

Attorney Docket No. **DVDOP015**

First Named Inventor:

THOMPSON, Laurence A.

jc530 U.S. PTO
09/478122
01/05/00**UTILITY PATENT APPLICATION TRANSMITTAL (37 CFR § 1.53(b))**

Assistant Commissioner for Patents
Box Patent Application
Washington, DC 20231

☐ Duplicate for
fee processing

Sir: This is a request for filing a patent application under 37 CFR § 1.53(b) in the name of inventors:
Laurence A. Thompson

For: **AUDIO SIGNAL DELAY APPARATUS AND METHOD**

Application Elements:

- ☒ 17 Pages of Specification, Claims and Abstract
☒ 06 Sheets of Informal Drawings
☐ 02 Pages Combined Declaration and Power of Attorney

Accompanying Application Parts:

- ☐ Assignment and Assignment Recordation Cover Sheet (recording fee of \$40.00 enclosed)
☐ 37 CFR 3.73(b) Statement by Assignee
☐ Information Disclosure Statement with Form PTO-1449
☐ Copies of IDS Citations
☐ Preliminary Amendment
☒ Return Receipt Postcard
☐ Small Entity Statement(s)
☐ Other:

Fee Calculation (37 CFR § 1.16)

	(Col. 1) NO. FILED	(Col. 2) NO. EXTRA	SMALL ENTITY RATE	FEE	OR	LARGE ENTITY RATE	FEE
BASIC FEE			\$380	\$	OR	\$760	\$
TOTAL CLAIMS	34	-20 = 14	x09 =	\$	OR	x18 =	\$
INDEP CLAIMS	02	-03 = 00	x39 =	\$	OR	x78 =	\$
[] Multiple Dependent Claim Presented			\$130 =	\$	OR	\$260 =	\$
* If the difference in Col. 1 is less than zero, enter "0" in Col. 2.			Total	\$	OR	Total	\$

☐ Check No. in the amount of **\$ 40.00** is enclosed.

☒ The Commissioner is authorized to charge any fees beyond the amount enclosed which may be required, or to credit any overpayment, to Deposit Account No. 50-0384 (Order No. DVDOP015).

General Authorization for Petition for Extension of Time (37 CFR §1.136)


☒ Applicants hereby make and generally authorize any Petitions for Extensions of Time as may be needed for any subsequent filings. The Commissioner is also authorized to charge any extension fees under 37 CFR §1.17 as may be needed to Deposit Account No. 50-0384 (Order No. DVDOP015).

☒ Please send correspondence to the following address:

HICKMAN STEPHENS COLEMAN & HUGHES, LLP
P.O. Box 52037
Palo Alto, CA 94303-0746

Tel (650) 470-7430
Fax (650) 470-7440

Date: 1/5/00



Douglas E. Mackenize
Registration No. 38,955

AUDIO SIGNAL DELAY APPARATUS AND METHOD

By Inventor:

Laurence A. Thompson

5

FIELD OF THE INVENTION

The present disclosure relates to video and audio circuits and more particularly to circuits that provide a delay in an audio signal and further to circuits that synchronize
10 audio signals with video signals.

BACKGROUND OF THE INVENTION

Household video technology began decades ago with an analog station-
15 transmitted video signal, a roof top antenna, and a three channel black and white television set in a living room. Since then, video technology has experienced rapid growth due to advances in microprocessor, communications, and digital signal processing technology. In addition to the standard television, the video market has expanded to include video cassette recorders (VCR), multiple providers of satellite television, digital
20 cable, video on-demand cable, digital television, hi-definition television, overhead projection television, home movie theaters, camcorder video units and many other video options. As technology continues to develop, the list of video options available to the consumer will continue to grow as well.

25 The vast video market has led to an expansion of video formats currently in use by these different products. In fact, some products have more than one video format. For example, digital television transmission has been approved and is in operation in the United States. The standard for digital television includes 18 new video formats.

30 The increasing number of video products and corresponding video formats has created a problem of compatibility between products. In order to experience video from

one format in another format, the video stream must be processed and transformed into the desired format. For example, to view video formatted according to the interlaced scanning scheme used in analog television standards on a computer display that uses progressive scanning, a format transformation must be performed.

5

Before this transformation occurs, a video signal and its corresponding audio signal are synchronized to temporally correspond to each other. As a result of the format transformation, the required signal processing introduces an undesirable delay in the video stream, causing the video and audio streams to be unsynchronized. That is, as a result of the transformation, conversations and sound effects in the video may not match a speaker's mouth or events as they occur. Furthermore, as signals are processed through more than one device, this delay becomes greater and more noticeable to the viewer. The transformation processing therefore requires that the video and audio signal be re-synchronized to eliminate the undesirable mismatching of the video and audio signals.

15

A delay introduced in the audio signal provided to synchronize the audio and video signal is dependent upon the format of the video and corresponding audio signal. As discussed above, a number of formats are used for digital video signals. These formats accommodate variable audio sampling rates and sample sizes. Furthermore, digital audio signals are commonly transported from one processing device to another within an audio/video processing product using a number of serial transmission schemes. These schemes use various methods to mark the start of a sample or determine left from right in a stereo pair. One example of such a serial audio stream is a standard known as I²S. As such, different types of digital audio signals require a different delay in order to be properly re-synchronized to their corresponding processed video signal.

25

Circuits that adjust an audio signal to account for the delay required by video signal processing are well known in the art. However, past solutions of the prior art consist of circuits that provide a delay in the audio signal only for video transformed from one specific format to another. In order to provide the appropriate audio delay for different video format transformations using the solutions in the prior art, several circuits

30

5 process.

	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26	27	28	29	30	31	32	33	34	35	36	37	38	39	40	41	42	43	44	45	46	47	48	49	50	51	52	53	54	55	56	57	58	59	60	61	62	63	64	65	66	67	68	69	70	71	72	73	74	75	76	77	78	79	80	81	82	83	84	85	86	87	88	89	90	91	92	93	94	95	96	97	98	99	100
1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26	27	28	29	30	31	32	33	34	35	36	37	38	39	40	41	42	43	44	45	46	47	48	49	50	51	52	53	54	55	56	57	58	59	60	61	62	63	64	65	66	67	68	69	70	71	72	73	74	75	76	77	78	79	80	81	82	83	84	85	86	87	88	89	90	91	92	93	94	95	96	97	98	99	100	

SUMMARY OF THE INVENTION

5 A disclosed embodiment solves the problem of providing a delay in a digital serial audio signal corresponding to the particular format of audio signal while minimizing the required hardware. The disclosed embodiment determines the audio sample size and sample rate by comparing the frequency of the serial audio clock to a known reference frequency. It also uses the serial clock to sample the serial audio data
10 signals. It then stores the stream of data in a memory which is configured as a circular buffer having a write pointer and a read pointer. The address space between the pointers corresponds to a particular time delay in the data, for example, as the differences in the address increases, so does the delay in reading the data relative to when it was written. The serial audio clock is then used again to output the serial audio data signals such that a
15 delay in the serial digital audio data stream is achieved.

BRIEF DESCRIPTION OF THE DRAWINGS

5 FIG 1 is a block diagram of the prior art providing a delay for multiple formats of digital audio signals.

FIG 2 is a block diagram of the audio delay apparatus.

10 FIG 3 is a block diagram of the audio delay circuit.

FIG 4 is a flow chart of the operation of the audio delay circuit.

FIG 5 is a block diagram of the audio format detection circuit.

15 FIG 6 is a flow chart of the operation of the audio format detection and write address generation circuit.

DETAILED DESCRIPTION

As shown in FIG. 2, AN audio delay circuit generally designated 95 includes an input device 700, a processing device 800, and an output device 900. The input device 700 is receptive to an incoming audio signal 701. As is known in the art the audio signal may be composed of numerous separate component signals. In the present embodiment, the audio signal includes a serial data signal, a frame synchronization signal, and a clock signal. The frame synchronization signal may have many formats and variations and is referred to by different names depending upon the product provider. This disclosure uses the term “frame synchronization signal” as a broad term meant to include signals such as left and right stereo signals, single pulse signals, data packet start signals, and any other signal that marks the beginning of a packet of data in the audio signal. As is known in the art there are many terms used to label this type of signal and they are all incorporated as the term frame synchronization signal is used in the present disclosure.

As shown in FIG. 3, the audio delay circuit 95 further includes a FIFO register 10, an audio format detection circuit 20, a memory controller circuit 30, a memory chip 40, a write address generator 50, a read address generator 60, a control state machine 70, and an audio data input FIFO 80.

With the reference of FIG. 4, the circuit flow generally designated 1000 generally includes an operation 100 in which data signals are input into the FIFO register 10, an operation 200 in which data signals are stored in a memory circuit, an operation 300 in which the audio signal format is detected, an operation 400 in which the audio signal delay is implemented according to the audio signal's detected format, an operation 500 in which the data signals are retrieved from memory, and an operation 600 in which the data signals are output with the proper delay implemented.

The operation of the audio delay circuit 95 as shown in FIG 3 will now be described. Circuit operation begins with the Audio Data Input FIFO 10 receiving the

data signal clock and accompanying data signals. In a preferred embodiment, the data signals received are a serial data signal through data line 2, a frame synchronization signal through data line 4, and an audio clock signal through data line 6. Packets of data or frames from the data signals accompanying the audio clock signal are loaded into the FIFO register 10. The size of FIFO register 10 is determined by the requirements of the memory system and the highest data flow rate to be accommodated and is generally unrelated to any specific digital serial audio format. The FIFO register 10 performs serial to parallel conversion of the digital serial audio data and provides temporary storage of the data until a memory write cycle is requested. When FIFO register 10 is full, the FIFO register 10 sends a FIFO full signal to the control state machine 70 through FIFO full data line 14.

Upon receiving the FIFO full signal, the control state machine 70 sends a write request to the memory controller 30 through read/write request data line 72. Upon receiving this request, the memory controller 30 puts the request in a queue (not shown) and when other memory transactions are complete, the memory controller 30 sends a signal to the input FIFO register 10 which causes the FIFO register 10 to drive its contents into the memory data bus 42 and into memory chip 40 under control of the memory controller 30 using control and address signals 44.

The format detection process will now be described. The format of the audio signal is detected by the audio format detection circuit 20 shown in FIG 3. The audio format detection circuit 20 is depicted in more detail in FIG. 5 and its operation is shown in the flow chart of FIG 6. As shown in FIG 5, the circuit 20 includes a divide-by-constant-counter 210, which in the preferred embodiment has a constant of 16, clocked by the audio shift clock (SCK) 8, a circuit 220 to synchronize the divide-by-constant signal to a 27 MHz clocking domain, a counter 230 clocked by 27 MHz, a latch 240 to store the previous state of the counter 230, a comparing circuit 250 containing comparators 251 through 258 which compare the stored count to predetermined values, a lookup memory circuit 260, a write address latch 270, and a comparator 280.

With the reference of FIG. 6, the format detection circuit flow generally designated 300 generally includes an operation 310 in which the frequency of the audio shift clock is divided by a constant which in the preferred embodiment is equal to 16 to create a SCK/16 signal, an operation 320 in which the SCK/16 and 27 MHz clock are synchronized and edge detection occurs, an operation 330 in which the SCK/16 clears a counter and enables a latch to store the previous count, an operation 340 in which the latched count is compared to constants, the result of the comparison used to select a Write Address, an operation 350 in which a write address is latched, an operation 360 in which the current and last Write Address are compared, an operation 380 in which no action is required if the last and current Write Address are equal, and an operation 390 in which the Read Address Pointer is initialized and the current Write Address is loaded into the Write Address Pointer.

The audio format detection circuit 20 receives the audio clock signal (SCK) through data line 8 and a reference clock signal through data line 21. The SCK input clocks a 4 bit counter 210, which generates a timing signal on data line 212 whose frequency is equal to SCK/16. This signal is sent through a synchronization and edge detection circuit 220, where it is synchronized to the 27MHz clock domain. The output of the synchronizer 220 is a pulse on data line 214 whose frequency is nominally equal to SCK/16 and whose pulse width is equal to one period of the 27MHz clock. This pulse becomes a master timing signal. The following events occur once per period of this master timing signal.

The timing pulse clears a counter 230 which is clocked by 27MHz. The pulse also enables a latch 240 which stores the previous state of the counter 230. The latch 240 now contains a binary number corresponding to the number of cycles of the 27MHz clock that occurred in the period SCK/16.

Comparators 251 through 258 compare the contents of the latch 240 to eight constant values which correspond to various SCK frequencies. The results of the comparisons are used to select one of eight predetermined Write Address values which is

captured in latch 270 such that the Write Address calculated in the previous period is compared to the Write Address calculated in the current period by the comparator 280.

If the Previous and Current Write Address values are equal, then the frequency of the SCK has not changed and no further action is required. However, if the Previous and Current Write Addresses are not equal, then the SCK frequency has changed, and the memory Read and Write Pointers must be initialized. The Read Address pointer is initialized with a constant, and the Write Address pointer is initialized with the Current Write Address calculated as described above. It will be apparent to one skilled in the art that the operations described thus far may be accomplished in a variety of ways, including but not limited to initializing the Write Address pointer with a constant and initializing the Read Address with a constant correlating to the detected format of the audio signal.

The delay for the audio signal is implemented by configuring a memory register (not shown) within the memory controller 30 corresponding to the detected format of the sampled audio clock signal. As described above, each constant value within the comparator circuit 250 referenced above corresponds to an offset value. This offset value is used to configure an address pointer that then configures the memory register. The memory register, configured by the address pointer corresponding to the detected format, forms the delay required by the particular audio format. The memory register is defined with a first parameter and a second parameter. In one embodiment, the memory register is a buffer (not shown), the first parameter is a write address pointer and second parameter is a read address pointer. The write address offset information is provided by the audio format detection circuit 20 through data line 22 to the write address generator circuit 50.

Next, the memory controller 30 configures a write address pointer and a read address pointer. Information for these pointers is provided from the write address generator circuit 50 through data line 52 and the read address generator circuit 60 through data line 62. When the memory controller 30 receives the write address generator

information, it resizes the buffer according to the configured write address and the read address pointers. The memory controller 30 then implements the delay corresponding to the resized buffer.

5 The memory controller 30 sends a control signal on data line 44 to the memory chip 40 to send the stored data signal and frame synchronization signal through the memory data bus 42. The memory controller 30 then reads the signals sent over the data bus 42. If the audio data input FIFO 80 is presently empty, a FIFO empty signal is sent from the FIFO register 80 to the control state machine 70 through data line 82. In
10 response to this signal, the control state machine 70 sends a read request signal through data line 72 to the memory controller 30. Upon receiving this request, the memory controller 30 puts the request in a queue (not shown), completes other memory transactions, and finally sends a signal to the memory chip 40 using data line 44 which causes data to be read from the memory chip 40 and written to the input FIFO 80 under
15 control of the memory controller 30. The input FIFO 80 then performs a parallel to serial conversion and sends its contents to outputs through data lines 84, 86 and 88 under control of the Serial Audio Clock (SCK).

 In use, the disclosed circuit 90 provides for a delay in the audio signal
20 corresponding to the particular format of audio signal while minimizing the required hardware. The disclosed embodiment determines the audio sample size and sample rate by comparing the frequency of the serial audio clock to a known reference frequency. It also uses the serial clock to sample the serial audio data signals. It then stores the stream of data in a memory which is configured as a circular buffer having a write pointer and a
25 read pointer. The serial audio clock is then used again to output the serial audio data signals such that a delay in the serial digital audio data stream is achieved.

 Having thus described illustrative embodiments of the invention, it will be apparent that various alterations, modifications and improvements will readily occur to
30 those skilled in the art. Such obvious alterations, modifications and improvements, though not expressly described above, are nonetheless intended to be implied and are

[illegible]

CLAIMS

What is claimed is:

- 5 1. An apparatus for delaying an audio signal comprising:
an input device receptive to an audio signal having one of a plurality of formats;
a processing device coupled to the input device, the processing device configured
for providing a delay in the audio signal corresponding to the format of the audio signal;
and
10 an output device coupled to the processing device, the output device configured to
output the audio signal with the delay corresponding to the format of the audio signal.
- 15 2. The apparatus as claimed in claim 1, wherein the audio signal further comprises a
serial audio clock signal and a plurality of accompanying signals.
3. The apparatus as claimed in claim 2, wherein the accompanying signals further
comprises a data signal and a frame synchronization signal.
- 20 4. The apparatus as claimed in claim 2, wherein the accompanying signals are
loaded into a register.
5. The apparatus as claimed in claim 4, wherein the register is a FIFO register.
- 25 6. The apparatus as claimed in claim 4, wherein the accompanying signals are stored
in a memory device.
- 7 The apparatus as claimed in claim 6, wherein the memory device further
comprises a memory controller and a memory chip.

8. The apparatus as claimed in claim 1, wherein the processing device further comprises an audio format detection device operable to detect the format of the audio signal.

9. The apparatus as claimed in claim 8, wherein the audio format detection device is operable to detect a number of edge transitions in the serial audio clock signal and provide a corresponding detected count.

10. The apparatus as claimed in claim 9, wherein the audio format detection device further comprises a plurality of model data, wherein each model data represents one of the plurality of audio signal formats and a corresponding one of a plurality of delay data, wherein the detected count is compared to the model data, the audio format detection device operable to provide the delay data representing the model data that is equal to the detected count.

11. The apparatus as claimed in claim 10, wherein the processed clock signal is synchronized to a reference clock.

12. The apparatus as claimed in claim 8, wherein the audio format detection device is operable to provide a processed clock signal by dividing the serial audio clock signal by a constant.

13. The apparatus according to claim 12, wherein the processing device is operable to compare a new delay data to an old delay data, the processing device operable to reconfigure a buffer if the new delay data is not equal to the old delay data.

14. The apparatus as claimed in claim 10, wherein the detected count is compared to the model data by a plurality of comparators.

15 The apparatus as claimed in claim 10, wherein the provided delay data is a first offset value, the processing device operable to resize a write address pointer with the offset value.

5 16. The apparatus as claimed in claim 10, wherein the provided delay data is a second offset value, the processing device operable to resize a read address pointer with the offset value.

10 17. The apparatus as claimed in claim 10, wherein the processing device further comprises a memory unit to provide the delay corresponding to the delay data.

15 18. The apparatus as claimed in claim 15, wherein the processing device further comprises a first parameter and a second parameter, the first parameter configured according to the provided delay data.

19. The apparatus as claimed in claim 18, wherein the first parameter is a write address parameter, the second parameter is a read address parameter, and the memory unit is a buffer.

20 20. A method for delaying an audio signal comprising the steps of:
receiving an audio signal having one of a plurality of formats;
processing the audio signal to provide a delay corresponding to the format of the received signal; and
providing the audio signal with the delay corresponding to the format of the
25 signal.

21. The method of claim 22, wherein the audio signal further comprises a serial audio clock signal and accompanying signals.

22. The method of claim 21, wherein the step of processing the audio signal further comprises the step of providing a processed serial audio clock signal, the processed serial audio clock signal provided by dividing the serial audio clock signal by a constant.

23. The method of claim 21, wherein the accompanying signals further comprise a frame synchronization signal and a data signal.

24. The method of claim 21, wherein the step of processing the audio signal further comprises the step of storing the accompanying signals in a memory device.

25. The method of claim 24, wherein the memory device further comprises a memory chip and a memory controller.

26. The method of claim 22, wherein the step of processing audio signal further comprises the step of detecting the format of the audio signal.

27. The method of claim 26, wherein the step of detecting the format of the audio signal further comprises the steps of detecting the number of edge transitions in the processed serial audio clock signal and providing a detected count.

28. The method of claim 27, wherein the step of detecting the format of the audio signal further comprises the steps of providing a plurality of model data, wherein each model data corresponds to a serial audio clock signal format, providing a plurality of delay data, wherein each delay data corresponds to a model data, comparing the detected count to the plurality of model data and providing the delay data corresponding to the model data equal to the detected count.

29. The method of claim 28, further comprising the step of comparing the detected count to the plurality of model data using comparator circuits.

30. The method of claim 28, wherein the detected count further comprises the number of edge transitions in the processed serial audio clock signal within a period, and wherein the plurality of model data include the number of edge transitions present in each processed serial audio clock signal format in the period.

5

31. The method of claim 30, wherein the step of processing the audio signal further comprises the step of providing a memory register having a first parameter and a second parameter, the memory register configured to provide a delay.

10 32. The method of claim 31, wherein the step of providing a memory register further comprises the step of providing an offset, the offset corresponding to the model data equal to the detected count and resizing the memory register by providing the offset for the first parameter.

15 33. The method of claim 32, wherein the first parameter is a write address pointer, the second parameter is a read address pointer, and the memory register is a buffer.

34. The method of claim 33, wherein the first parameter is a read address pointer, the second parameter is a write address pointer, and the memory register is a buffer.


20

ABSTRACT OF THE DISCLOSURE


An apparatus for delaying an audio signal in conformance with the format of the audio signal. An input device is receptive to an audio signal having one of a plurality of
5 formats. A processing device coupled to the input device is operable to provide a delay in the audio signal corresponding to the format of the audio signal. The delayed audio signal is output through an output device. An audio format detection circuit is operable to detect the number of edge transitions within a known period in a processed audio
10 signal and thereby determine the format of the audio signal by comparing a detected edge transition count to model data representative of the plurality of formats.

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214
2215
2

AUDIO
INPUT DATA SIGNAL
OF FORMAT A



INPUT AUDIO DATA
SIGNAL OF FORMAT B



INPUT AUDIO DATA
SIGNAL OF FORMAT C




FIG. 1

PRIOR ART

95





FIG. 2



Audio Delay Circuit Block Diagram
 L. Thompson 12/2/99
 DVDO, Inc. Confidential

FIG. 3




FIG. 4




FIG. 5




FIG. 6